

Technical:

Voltage: AC100-240V 50/60HZ

Power supply: 50W

Light Source 1: 7*10W RGBW 4 IN 1 LED

Channel: 7/11CH

Operation: DMX512, Auto, Sound, Master-slave



AdkinsProLighting.com

FLAT PAR FX

7 X 10W LED With FX Ring



User's Manual

(330) 436-3260 Fax: (330) 436-3283

E-mail: support@adkinsprolighting.com

www.adkinsprolighting.com

Menu Functions

#	content	scale	Function and description
1	A001	001- 512	DMX512 Address code setting
2	7cH	7/11	Channel mode setting , 7CH,11CH
3	Au/Soud	1-10	1-9 Preset effect , Sound = Sound control effect
4	SP00	00-16	Auto program speed selection
5	F255	000 - 255	More than 1 start stroboscopic, speed from slow to fast
6	r255	000 - 255	R dimming, from dark to bright
7	G255	000 - 255	G dimming, from dark to bright
8	b255	000 - 255	B dimming, from dark to bright
9	u255	000 - 255	W dimming, from dark to bright

Table (1) function comparison table of digital tube display window

7 Channel Mode

channel	function	explain
---------	----------	---------

CH1	R	R Dimming, from dark to bright
CH2	G	G Dimming, from dark to bright
CH3	B	B Dimming, from dark to bright
CH4	W	W Dimming, from dark to bright
CH5	Lamp belt R	Outer ring R dimming, from dark to bright
CH6	Lamp belt G	Outer ring G dimming, from dark to bright
CH7	Lamp belt B	Outer ring B dimming, from dark to bright

11 Channel Mode

channel	function	explain
CH1	Total dimming	Master Dimmer, from dark to bright
CH2	Total stroboscopic	Master stroboscopic 005-255 from slow to fast
CH3	Function select	000-005 : CH1-CH6 control. 006-229 : Built-in effect; 230-255 : Audio Mode
CH4	Effect speed	Built-in effect of moving speed, from slow to fast, sound control sensitivity adjustment
CH5	R	R Dimming, from dark to bright

CH6	G	G dimming, from dark to bright
CH7	B	B dimming, from dark to bright
CH8	W	W dimming, from dark to bright
CH9	Lamp belt R	Outer ring R dimming, from dark to bright
CH10	Lamp belt G	Outer ring G dimming, from dark to bright
CH11	Lamp belt B	Outer ring B dimming, from dark to bright