

## 15Channels Mode

Channel	Function	Description
1	Pan	0-255
2	Tilt	0-255
3	Tilt infinite rotation	0-255
4	Pan/Tilt Speed	6-255
5	Master dimming	0-255
6	Strobe	10-249
7	RED12 master dimming	0-255
8	GREEN12 master dimming	0-255
9	BLUE12 master dimming	0-255
10	WHITE12 master dimming	0-255
11	Motor Auto	16-255
12	Motor Auto Speed	0-255
13	Color Auto	8-255
14	Color Auto Speed	0-255
15	RESET	250-255 (5 seconds)

### Technical :

Voltage : AC100—240V, 50/60HZ

Power : 160W

Light source : 12PCS\*10W

Channel : 21/15CH ;

Control Mode : DMX512, master-slave, auto, sound



AdkinsProLighting.com

# MH CUBE

12 X 10W LED Moving Head Cube



## User's Manual

(330) 436-3260 Fax: (330) 436-3283  
E-mail: support@adkinsprolighting.com

www.adkinsprolighting.com

**Menu Function:**

Addr	A001-A512	512 Address Setting
CHnd	21CH	21 Channel Setting
	15CH	15 Channel Setting
SLnd	AUTO	Master Auto Mode
	Soun	Master Sound Mode
	SL 1	Slave DMX Controller Mode
	SL 2	Slave Mode
SHnd	SH 0	Effect0 (Recommend)
	SH 1	Effect1
	SH 2	Effect2
	SH 3	Effect3
SEnS	0-99	Sound Sensitivity Adjustment
bLAnd	bLAc	No 512 signal return to zero
	Auto	No 512 signal Auto
	Soun	No 512 signal Sound
	HoLd	No 512 signal Keep the controller state of last time
LEd	OFF	Close the screen after 5 seconds
	ON	The screen open all the time
dISP	no	Display reverse
	YES	Display forward
rPAN	no	Normal pan operation
	YES	Reverse pan operation
rTiL	no	Normal tilt operation
	YES	Reverse tilt operation
REST	YES	System reset

**21 Channel Mode:**

Channel	Function	Description
1	Pan	0-255
2	Pan fine adjustment	0-255
3	Tilt	0-255
4	Tilt fine adjustment	0-255
5	Vertical infinite adjustment	6-127 forward
		128-255 reversal
6	horizontal and vertical speed	0-255
7	Master dimming	0-255
8	Strobe slow to fast	10-249
9	RED 1 master dimming	0-255
10	GREEN 1 master dimming	0-255
11	BLUE 1 master dimming	0-255
12	WHITE 1 master dimming	0-255
13	RED 2 master dimming	0-255
14	GREEN 2 master dimming	0-255
15	BLUE 2 master dimming	0-255
16	WHITE 2 master dimming	0-255
17	Motor Auto	16-128
	Sound	129-255
18	Motor Auto Speed,slow to fast;sound sensitive slow to fast	0-255
19	color Auto	1-140
	Sound	141-255
20	Color auto Speed;sound sound sensitive slow to fast	0-255
21	RESET	250-255 (5 seconds)