

Technical:

Voltage: AC90-220V 50/60HZ

Power : 50W

Light Source: Cree Warm White Led
3W*12pcs+SMD5050 LED 72pcs

Operation: DMX512, Auto, Sound, Master-slave



AdkinsProLighting.com

COLOR BAR FX

12x3W + 72pcs SMD LED



User's Manual

(330) 436-3260 Fax: (330) 436-3283

E-mail: support@adkinsprolighting.com

www.adkinsprolighting.com

LED 2 in1 WALL WASH Light

No.	Channel	Channel Data	Function instruction
1	CH9	06/09/84/89	DMX channel mode setting
2	d001	001- 512	DMX512 address setting
3	R255	000 - 255	3in1 red dimmer
4	G255	000 - 255	3in1 green dimmer
5	B255	000 - 255	3in1 blue dimmer
6	H255	000 - 255	Single white dimmer
7	Pr01	1 - 30	Preset effect
8	SP16	00 - 20	Speed setting
9	Auto	Auto/Audi	Testing mode, switching between auto run and sound by pressing button A/B
10	DISP	/	Display setting

DMX Channel description

6 Channel Mode

CH	function	instruction
CH1	000-255	Dimmer
CH2	000-255	Strobe
CH3	000-255	3in1 R red dimmer
CH4	000-255	3in1G green dimmer
CH5	000-255	3in1B blue dimmer
CH6	000-255	Y Yellow dimmer

9 Channel Mode

CH	function	instruction
CH1	000-255	Dimmer
CH2	005-255	Strobe
CH3	000-255	3in1 R red dimmer
CH4	000-255	3in1G green dimmer
CH5	000-255	3in1B blue dimmer
CH6	000-255	Y Yellow dimmer
CH7	001-255	Color mixing
CH8	001-255	Preset effect selection
CH9	000-255	speed

84 Channel Mode

CH	function	instruction
CH1	000-255	Y1 yellow dimmer
CH2	005-255	Y2 yellow dimmer
...
CH11	006-255	Y11 yellow dimmer
CH12	000-255	Y12 yellow dimmer
CH13	000-255	1# 3in1 R red dimmer
CH14	000-255	1# 3in1G green dimmer
CH15	000-255	1# 3in1B blue dimmer
CH16	000-255	2# 3in1 R red dimmer
CH17	000-255	2# 3in1G green dimmer
CH18	000-255	2# 3in1B blue dimmer
...	

CH82	000-255	24# 3in1 R red dimmer
CH83	000-255	24# 3in1G green dimmer
CH84	000-255	24# 3in1B blue dimmer

89 Channel Mode

CH	function	instruction
CH1	000-255	dimmer
CH2	005-255	strobe
CH3	000-255	Y1 yellow dimmer
CH4	005-255	Y2 yellow dimmer
...
CH13	006-255	Y11 yellow dimmer
CH14	000-255	Y12 yellow dimmer
CH15	000-255	1# 3in1 R red dimmer
CH16	000-255	1# 3in1G green dimmer
CH17	000-255	1# 3in1B blue dimmer
CH18	000-255	2# 3in1 R red dimmer
CH19	000-255	2# 3in1G green dimmer
CH20	000-255	2# 3in1B blue dimmer
...	
CH84	000-255	24# 3in1 R red dimmer
CH85	000-255	24# 3in1G green dimmer
CH86	000-255	24# 3in1B blue dimmer
CH87	001-255	Color mixing
CH88	001-255	Preset effect selection
CH89	000-255	speed